



LoopSign external player LS-830



Hardware	
Processor / Ram / Flash	A83T Octa-Core 2GHZ / 1GB RAM / 8GB Flash
Size	196mm x 104mm x 30mm
Operating System	Android 6.0
Network Support	Wifi, RJ45 10/100 and optional 4G
USB2.0 ports	2 USB Host
SD card	Yes
Audio	Yes, mini jack
HDMI Output	1, 1080P
RTC Clock	Yes

Start Url

https://loopsign.no/screen/20/mp4

Reboot at

00:00

Refresh at

Never

Pin

Proxy

Enable ☐

Host

Port


LoopSign Player version 1.5

LoopSign Player is intended for use with Loop24 products

<http://loop24.no>

Loop24 AS

All rights reserved



To enter this settings page from full screen LoopSign Player

Click top left corner and enter pincode

NEXT



Loop24 AS, Ullern Allé 28, 0381 Oslo - Norway
+47 23 25 25 25, info@loop24.no

