

Datasheet

MX 600



MX 610



MX 700



WALL OUTLETS

Features

SAT/TV/Radio
NO Loop through
Easy installation
Wide frequency

Technical specifications

Insertion loss - FM
87.5 - 108 MHz Max 3.5 dB

Insertion loss - SAT
950 - 2150 MHz Max 3.5 dB

Insertion loss - TV
40 - 68 MHz Max 4.5 dB
120 - 174 MHz Max 5.5 dB
174 - 862 MHz Max 4 dB

Dimensions and weight:

Unit (WxDxH): 76x48x76 mm
Unit (Net weight): 0.13 Kg
Giftbox (WxDxH): 115x80x50 mm
Gross Weight: 0.15 Kg

EAN number: 5706998010025
Item number: 1208
Carton QTY: 80

Contents:

Wall outlet
4 x screws.

Features

SAT/TV/Radio
Loop through
Easy installation
Wide frequency

Technical specifications

Insertion loss
In/Out Max 4.0 dB

Insertion loss - FM
87.5 - 108 MHz Max 3.5 dB

Insertion loss - SAT
950 - 2150 MHz Max 3.5 dB

Insertion loss - TV
40 - 68 MHz Max 4.5 dB
174 - 700 MHz Max 5.5 dB
700 - 862 MHz Max 4 dB

Dimensions and weight:

Unit (WxDxH): 76x48x76 mm
Unit (Net weight): 0.13 Kg
Giftbox (WxDxH): 115x80x50 mm
Gross Weight: 0.15 Kg

EAN number: 5706998010032
Item number: 1210
Carton QTY: 80

Contents:

Wall outlet
4 x screws.

Features

2xSAT / TV / Radio
Easy installation
Wide frequency

Technical specifications

Insertion loss - FM
87.5 - 108 MHz Max 3.5 dB

Insertion loss - SAT
950 - 1500 MHz Max 4.5 dB
1500 - 2050 MHz Max 5 dB
2050 - 2150 MHz Max 3.5 dB

Insertion loss - TV
5 - 68 MHz Max 3 dB
174 - 450 MHz Max 4.5 dB
450 - 800 MHz Max 3 dB
800 - 862 MHz Max 4.5 dB

Dimensions and weight:

Unit (WxDxH): 76x48x76 mm
Unit (Net weight): 0.13 Kg
Giftbox (WxDxH): 115x80x50 mm
Gross Weight: 0.15 Kg

EAN number: 5706998010049
Item number: 1212
Carton QTY: 80

Contents:

Wall outlet
4 x screws.